

## Technical Reference - Q&A

**1. Q: I have a motherboard with Realtek HD audio codec. After resume Windows Vista from sleep or from hibernation, the high definition audio device may no longer work. How do I solve this?**

**A:** This is caused by Microsoft. It can be solved by installing the Microsoft Hot fix. Please refer to the Microsoft Knowledge Base:  
<http://support.microsoft.com/kb/929685/en-us>

**2. Q: My motherboard is ConRoe1333-DVI/H R2.0. Are there recommended memory configurations for my motherboard?**

**A:** Please refer to page 17 of user's manual.  
<http://download.asrock.com/manual/ConRoe1333-DVIH%20R2.0.pdf>

### Recommended Memory Configurations (DS: Double Side, SS: Single Side)

	DDRII_1 (Yellow Slot)	DDRII_2 (Orange Slot)	DDRII_3 (Yellow Slot)	DDRII_4 (Orange Slot)
1 memory module	DS/SS*	X	X	X
2 memory modules	DS/SS	X	DS/SS	X
2 memory modules	X	DS/SS	X	DS/SS
3 memory modules	SS	SS	DS/SS	X
4 memory modules	SS	SS	SS	SS

\* If you only install one memory module, you can install it to any one of the four slots.

These two TRANSCEND memory modules can only be supported under the following conditions:

DRAM VENDOR	SIZE (MB)	TYPE	CELL VENDOR	CELL NO.	SINGLE SIDE / DOUBLE SIDE
TRANSCEND	256	DDRII533	SAMSUNG	K4T56083QF-ZCD5	SINGLE SIDE
TRANSCEND	512	DDRII533	INFINEON	HYB18T512800AF37	SINGLE SIDE

1. If you plan to install one above memory module, you can install it to any DDRII slot of this motherboard.
2. If you plan to install two above memory modules, it is recommended to install them either in the set of yellow slots (DDRII\_1 and DDRII\_3), or in the set of orange slots (DDRII\_2 and DDRII\_4).
3. This motherboard does not support three or four above memory modules.